

Service Note		
Product	Description:	Service note no.
X-wiz	Mounting X-Wiz ADA card	770 10 T002

Reason for note:

Guideline for installing the Host board for the EQ-Station.

IMPORTANT:

This replacement should only be carried out by a skilled technician.

PARTLIST:

Stock number	Name	Quantity
601011011	0812- ESD BAG (203x305mm)	1
815031011	X-Wiz ADA (2in 2out) for service.	1
566034130	R6116-a M3x36,6mm Hexagonal Metal Spacer	1
566005035	M3x35mm Hexagonal Metal Spacer	1
562000040	M3x6mm PAN,self taping,contact point	1
77010T002	Service note no. 77010T002	1

Procedure:

1. TURN OFF POWER AND DISCONNECT POWER CORD.
 2. Remove the lid and the back panel from the EQ station, you'll have to dismount the left and right rack panels.
 3. Remove the small metal lid from the back panel slot were the ADA card will be mounted in.
 4. You can mount the new card **815031011** in the top or the lower slot just be aware of if there is an ADA card mounted in the lower slot then use the **566005035** spacer otherwise use the **566034130**.
 - a. If you mount the card in lower slot and there is no card above it then fasten the card with **562000040** screw.
 5. Fasten the card using the **562000040** screw.
- NOTE: If replacing an ADA card, remove the screw located in the middle of the card before removing it.**
6. Mount the back panel and lid again
 7. Power on the unit and make sure that the station locates the card when booting up, you should hear click sounds from the relays.
 8. END

If any trouble please contact us at Tech@tcelectronic.com

TC-Electronic support site: <http://tcsupport.custhelp.com/>

Good luck!