

Restriction nr4

This is a matrix over our different board combinations on C-series amps, you can expect to find that have compatibility problems, and the spare parts you should order when you encounter this amps.

	Combination 1			NOTE!!
	IN / OUTPUT-board	AMP-board	POWER SUPPLY-board	
Boards in your amp	AICO4 rev 06 or 07-FXXX	A25TD rev 08 or 09-FXXX	All SP100F-FXXX	This combination is not repairable outside the factory and must be returned to the Lab.gruppen factory for service.
order this spare parts	None	None	SP100F-FXXX (all versions)	

	Combination 2			NOTE!!
	IN / OUTPUT-board	AMP-board	POWER SUPPLY-board	
Boards in your amp	AICO4 rev 09-FXXX	A25TD rev 09-FXXX	All SP100F-FXXX	Chassies and output connectors must be changed when replacing AICO4 rev 10 and below with rev 11 and above
order this spare parts	AICO412e-FXXX	A25TD09-FXXX	SP100F-FXXX (all versions)	

	Combination 3			NOTE!!
	IN / OUTPUT-board	AMP-board	POWER SUPPLY-board	
Boards in your amp	AICO4 rev 09-FXXX	A25TD rev 11-FXXX	All SP100F-FXXX	Chassies and output connectors must be changed when replacing AICO4 rev 10 and below with rev 11 and above
order this spare parts	AICO412d-FXXX	A25TD11a-FXXX	SP100F-FXXX (all versions)	

	Combination 4			NOTE!!
	IN / OUTPUT-board	AMP-board	POWER SUPPLY-board	
Boards in your amp	AICO410d-FXXX	A25TD rev 11-FXXX	All SP100F-FXXX	Chassies and output connectors must be changed when replacing AICO4 rev 10 and below with rev 11 and above
order this spare parts	AICO412d-FXXX	A25TD11a-FXXX	SP100F-FXXX (all versions)	

	Combination 5			NOTE!!
	IN / OUTPUT-board	AMP-board	POWER SUPPLY-board	
Boards in your amp	AICO410e-FXXX	A25TD rev 13 or 14-FXXX	All SP100F-FXXX	Chassies and output connectors must be changed when replacing AICO4 rev 10 and below with rev 11 and above
order this spare parts	AICO412f-FXXX	A25TD16-FXXX-T	SP100F-FXXX (all versions)	