

fP14000

LAB.GRUPPEN

Part list

For safety critical components please contact Labgruppen for the right manufacturer							
Item number	Safety Critical	Item name	Replaces	Designator	Service level		
Power Supply		See restriction nr3 on how to find our item names			1	2	3
SMPS-A11-F07		SMPS-A11-F07 FCT	Replaces all SP140FXXX type F07 (see restriction nr1) because of deviations between 115V and 230V amps				x
T13KWF200VPM8770		Transformer 13kW Flyback 200V Core Pm8770	See restriction nr7 for new mounting instructions	K1			x
TCET1102G		Ic Photocoupler Tcet1102g		U2,U3,U4			x
PWMF107a-F01		Pulse Width Modulator Flyback 1 Rev.07a Final Assembly Type 01		U1			x
FPMSA		Front Panel Magnetic Shield Type A					x
400uHETD29ST		Inductor 400uH Etd29gsp		L1			x
BC549C		Transistor Bipolar Signal Bc549c		Q5,Q9			x
BC559C		Transistor Bipolar Signal Bc559c		Q7			x
BYM26E		Diode Power Switch Bym26e		D2, D5			x
6n8250VMMK5		Capacitor Polyester 6n8 250V Mmk 5mm		C12			x
STTA3006PI		Diode Power Stta3006pi 600v Isolated Dop3i		D16, D17			x
5V6.4W2%		Diode Zener 5V6 .4W 2%		D12,D13,D23,D24,D26, D27			x
MPSA42		Transistor Bipolar Signal Mpsa42		Q8			x
MPSA92		Transistor Bipolar Signal Mpsa92		Q10			x
BYT30PI1000		Diode Power Byt30pi1000 Isolated		D3			x
SGW25N120		Transistor Igbt Power Sgw25n120		Q1, Q2,Q3			x
12V.4W5%		Diode zener 12V.4w 5%		D19, D25			x
15V1.3W5%		Diode Zener 15V 1.3W 5%		D4			x
PN4392		Transistor Jfet Signal Pn4392		Q6			x
1N4148		Diode Signal 1n4148		D21, D22			x
STTA1512PI		Diode Power Stta1512pi 1200v Isolated Dop3i		D6			x

fp14000

LAB.GRUPPEN

Part list

input output							
AICO208-F01-T		AICO208-F01-T FCT	Replaces all AICO2XXX type F01				x
K-TBP60RED90		Kit Terminal Binding Post 60A Red 90dg	See restriction nr8 on how to mount the binding post				x
K-TBP60BLK90		Kit Terminal Binding Post 60A Black 90dg	See restriction nr8 on how to mount the binding post				x
LM317FP		Ic Voltage Regulator Lm317 Full Pack		U405			x
PCSPCO1A5V		Relay Pcb Singel Pole Change Over 1a 5v		RE402			x
74HCT4051D		Ic 2-input AND gate 74AHCT1G08 TSSOP-5		U410			x
HEF4094BT+-		Ic Comparator Lm393D SOIC-8		U414			x
NE8FA-H		Connector Ethercon 8+1pole Female+jack 90dg					x
2N7002		Transistor MOSFET 2N7002 SOT-23		Q3, Q5, Q103, Q105, Q205, Q203, Q303,Q305			x
BAW56		Diode Double BAW56 SOT-23		D3, D103			x
BC847C		Transistor Bipolar Signal BC847C SOT-23		Q1, Q101			x
BC857C		Transistor Bipolar Signal BC857C SOT-23		Q2, Q102			x
NE5532D		IC Operational Amplifier NE5532D SOIC-8		U5, U6, U105, U106,			x
BZX84C24		BZX84C24		D406,			x
TIP122FP		Transistor Bipolar Darlington Power Tip122 Fullpack		Q401			x

fp14000

LAB.GRUPPEN

Part list

Amp Board						
A70TD05-F03-T		A70TD05-F03-T FCT	Replaces all A70TDXXX type F03			x
MJW21195		Transistor Bipolar Power Mjw21195 To-247		Q1, Q2, Q3,Q4,Q5, Q6		x
MJW1302		Transistor Bipolar Power Mjw1302a		Q7		x
MJW3281		Transistor Bipolar Power Mjw3281a		Q11		x
MJW21196		Transistor Bipolar Power Mjw21196 To-247		Q12, Q13, Q14, Q15, Q16, Q17		x
STY60NK30Z		Transistor Mos Power Sty60nk30z		Q39, Q40, Q41, Q42		x
STTH1506DPI		Diode Power Sth1506dpi		D34, D37		x
PWMNATD-F01		Pwm Negative Side Amp. Class Td Final Assembly Type 01		U5		x
PWMPATD-F01		Pwm Positive Side Amp. Class Td Final Assembly Type 01		U6		x
MJE350I		Transistor Bipolar Signal Mje350 Insulated		Q8, Q18, Q19, Q24		x
MJE340I		Transistor Bipolar Signal Mje340 Insulated		Q9, Q10, Q20, Q31		x
15V1.3W5%		Diode Zener 15V 1.3W 5%		D14, D31, D40, D41		x
82R.6W1%		Resistor Metal Film 82r .6W 1%		R51, R19		x
1N5404		Diode Power 1n5404		D1, D10, D18, D27		x
BC549C		Transistor Bipolar Signal Bc549c		Q23, Q29, Q30, Q33, Q34, Q35, Q36, Q44, Q51		x
BC559C		Transistor Bipolar Signal Bc559c		Q22, Q25, Q27, Q28, Q32, Q45, Q50,		x
HCPL2601		Ic Photocoupler Hcpl2601		U3, U4		x
3V3.4W5%		Diode Zener 3V3 .4W 5%		D39, D43		x
15V1.3W5%		Diode Zener 15V 1.3W 5%		D14, D31, D40, D41		x
Q4040K7		Triac Q4040K7		Q38		x
T30AH250-6.3x32		T30AH250-6.3x32		P2, P3		x

fp14000

Part list

LAB.GRUPPEN

Mains input filter								For 115V amps
MIS13003-F04-T		MIS13003-F04-T FCT	Replaces all MISXXX type F04				x	See below
PCSPNO40A18V		PC SPNO 40A 18V		RE1			x	
PCSPCO10A12V		PC SPCO 10A 12V		RE2			x	
56R9W5%B		Resistor Wire Wound 56r 9W 5% Type B		R2			x	See below
T30AH250-6.3x32		Fuse Slow Blow 30a 250v 400a Ir 6.3x32mm		P7			x	See below
Chassis								
IFPC-PBLK		Interior fron panel type c painted black					x	
SPRB04-PBLK		Side Panel Right Type B, Rev.04 Painted Black					x	
SPLB04-PBLK		Side Panel Left Type B, Rev.04 Painted Black					x	
EFPC-ANBLK		Exterior front panel type c anodised black					x	
DCSRA04-PGRY		Dustfilter clip steel right type A rev.03 Painted Grey				x		
DCSLA04-PGRY		Dustfilter clip steel left type A rev.04 Painted Grey				x		
TCA-PBLK		Top Cover Type A Painted Black					x	
RPFP2F		Rear Panel Fp2-series Type F					x	

fp14000

Part list

LAB.GRUPPEN

115v							
Mains input filter							
MIS13003-F54-T		MIS13003-F54-T FCT	Replaces all MISXXX type F54				x
TBT4.5/6.3L31.5		Tube Brass Tinned 4.5/6.3 L31.5mm		P7			x
22R9W5%		Resistor wire wound 22r 9W 5%		R2			x
PCSPNO40A18V		PC SPNO 40A 18V		RE1			x
PCSPCO10A12V		PC SPCO 10A 12V		RE2			x
MLUS30A3x12AWG2 m		Mains Lead Usa 30a Plug Type Nema L5-30p 3xawg12 2m Black					X
Miscellaneous							
KNBD10H16POS		Knob D10 H16 black push-on slot					x
F80x25-24HSC		Fan 80x80x25mm 24VDC high speed type C					x
UI12Lx206a-F01		User Interface 12Lx2 rev06 vers.a Final Assembly type 01					x
K-RSC		Kit Rear Support type c				x	
SSDS5x72		Sticker selfadhesive double side 5x72mm					x
SRPFP14000-230C		Sticker Rear Panel FP14000 230V CE				x	
MLEU3x1.52mBLK		Mains Lead Eu Plug Type Cee7/vii 3x1.5mm2 2m Black					x
POT2B04		Pcb Potentiometer Board 2ch Type B rev.04					x
MH2x41ML		Mounting Header 2x4pole 1module Locking					x
VR10KLIN31HSBF		Pot 10k Lin 31step Horizontal Support Bracket Flatted shaft					x
M6MM9x2B		Mutter M9x2 typ B Del av VR10KLIN31HSBF					x

fp14000

LAB.GRUPPEN

Part list

BRB9.8x15x.5		Planbricka 9.8x15x.5 Del av VR10KLIN31HSBF					x
B580x523x150LAB3		Box 580x523x150mm type 0427 Cardboard White Lab.gruppen 3				x	
IBA		Interior Box type A 570x119x45mm				x	
OM-FP+		Operation Manual for FP+ series				x	
BUI		Board user interface					x
MLUS20A3x12AWG2 m		Mains Lead Usa 20a Plug Type Nema 6-20p 3xawg12 2m Black					x
PEPPCA		Packing EPP Corner type A				x	
SRFPFP14000-115EB		Sticker Rear Panel FP14000 115V ETL Certified rev.04	Sticker Rear Panel FP14000 115V ETL Certified Type B				x
SLABL03		Sticker Lab.gruppen Logotype rev.03				x	
SCAFCCMBGD		Sticker Caution Approvals FCC Must Be Grounded Type D					x
UIC2CHA-PGRY		Userinterface cover 2 channel type A painted grey					x
SMSFPP		Sticker mains switch fp plus				x	